

## **SWITCH MODULE** DCM 010 | DC 20 to 56 V



> High DC switching capacity> Variety of applications

**TECHNICAL DATA** 

> Wide DC voltage range > Simple connection

The switch module is used to control DC powered devices with high capacities in control and switch cabinets. It is controlled via an external potential-free contact (thermostat or hygrostat), which is connected between terminal 3 and 4. It must be ensured that the external contact is suitable to switch the required signal current without any problems.





Contact type	contact maker normally open (MOSFET)	
Service life	> 100,000 cycles	
Operating voltage	DC 20 to 56 V	
Control contact – signal current	3 mA at DC 20 V / 4.5 mA at DC 24 V 14 mA at DC 48 V / 17 mA at DC 56 V	
Connection	6-pole terminal: stranded wire <sup>1</sup> 1.5 mm <sup>2</sup> (AWG 16); max. 2.5 mm <sup>2</sup> (AWG 12)	
Mounting	clip for 35 mm DIN rail, EN 60715	
Casing	plastic according to UL94 V-O, grey (bicolor)	
Dimensions	93 x 53 x 44 mm	
Dimensions Weight	93 x 53 x 44 mm approx. 65 g	
	55 X 55 X 11 1111	
Weight	approx. 65 g	
Weight Fitting position	approx. 65 g vertical	
Weight Fitting position Operating temperature	approx. 65 g vertical see article table below	
Weight Fitting position Operating temperature Storage temperature	approx. 65 g vertical see article table below -40 to +80 °C (-40 to +176 °F)	
Weight Fitting position Operating temperature Storage temperature Operating / Storage humidity	approx. 65 g vertical see article table below -40 to +80 °C (-40 to +176 °F) max. 90 % RH (non-condensing)	

<sup>1</sup> When connecting with stranded wires, wire end ferrules must be used.





Heater





Art. No.	Max. switching capacity	Operating temperature
01010.0-00	DC 15 A	-40 to +40 °C (-40 to +104 °F)
01010.0-10	DC 13 A	-40 to +50 °C (-40 to +122 °F)
01010.0-20	DC 11 A	-40 to +60 °C (-40 to +140 °F)