

## **SMALL COMPACT THERMOSTAT**

## KTO 011 / KTS 011




- > Large setting range
- > Small size

- > Simple to mount
- > High switching performance


The mechanical thermostats KTO 011 and KTS 011 are two state regulators used to control heaters, coolers, filter fans or signal devices.

**KTO 011:** Thermostat (NC); contact breaker for regulating heaters. The contact opens when temperature is rising.

KTS 011: Thermostat (NO); contact maker for regulating of filter fans and heat exchangers or for switching signal devises when temperature limit has been exceeded. The contact closes when temperature is rising.



## Connection diagrams



Filter fan, Cooling equipment, Signal device





## TECHNICAL DATA


| Switch temperature difference | 7 K (±4 K tolerance)  |  |  |  |  |
|-------------------------------|---|--|--|--|--|
| Sensor element                | thermostatic bimetal  |  |  |  |  |
| Contact type                  | snap-action contact   |  |  |  |  |
| Service life                  | > 100,000 cycles  |  |  |  |  |
| Max. operating voltage        | AC 250 V (VDE)<br>AC 120 V (UL)   |  |  |  |  |
| Max. inrush current           | AC 16 A for 10 sec.   |  |  |  |  |
| Connection                    | 2-pole terminal, clamping torque 0.5 Nm max.:<br>rigid wire 2.5 mm <sup>2</sup> (AWG 14)<br>stranded wire <sup>1</sup> 1.5 mm <sup>2</sup> (AWG 16) |  |  |  |  |
| Mounting                      | clip for 35 mm DIN rail, EN 60715   |  |  |  |  |
| Casing                        | plastic according to UL94 V-O, light grey   |  |  |  |  |
| Dimensions                    | 60 x 33 x 43 mm   |  |  |  |  |
| Weight                        | approx. 40 g  |  |  |  |  |
| Fitting position              | variable  |  |  |  |  |
| Operating/Storage temperature | -45 to +80 °C (-49 to +176 °F)  |  |  |  |  |
| Operating/Storage humidity    | max. 90 % RH (non-condensing)   |  |  |  |  |
| Protection type               | IP20  |  |  |  |  |
|                               |   |  |  |  |  |

<sup>&</sup>lt;sup>1</sup> When connecting with wires, wire end ferrules must be used.

Important note: The contact system of the regulator is subjected to environmental influences, thus the contact resistance may change. This can lead to a voltage drop and/or self-heating of the contacts.







| Setting range  | Art. No.             | Art. No.           | Switcl   | hing current/capacit | Approvals    |     |                     |     |     |
|----------------|----------------------|--------------------|----------|----------------------|--------------|-----|---------------------|-----|-----|
|                | Contact breaker (NC) | Contact maker (NO) | AC 250 V | AC 120 V             | DC 24 - 72 V |     |                     |     |     |
| 0 to +60 °C    | 01140.0-00           | 01141.0-00         | 10 (2) A | 15 (2) A             | 30 W         | VDE | -                   | -   | EAC |
| -10 to +50 °C  | 01142.0-00           | 01143.0-00         | 10 (2) A | 15 (2) A             | 30 W         | VDE | UL File No. E164102 | -   | EAC |
| +20 to +80 °C  | 01159.0-00           | 01158.0-00         | 3 (2) A  | 3 (2) A              | 30 W         | VDE | UL File No. E164102 | CSA | EAC |
| +32 to +140 °F | 01140.9-00           | 01141.9-00         | 10 (2) A | 15 (2) A             | 30 W         | VDE | UL File No. E164102 | CSA | EAC |
| +14 to +122 °F | 01142.9-00           | 01143.9-00         | 10 (2) A | 15 (2) A             | 30 W         | VDE | UL File No. E164102 | CSA | EAC |
| 0 to +60 °C    | 01146.9-00           | 01147.9-00         | 10 (2) A | 15 (2) A             | 30 W         | VDE | UL File No. E164102 | CSA | EAC |